

SSL2103

Dimmable Greenchip controller for LED lighting

Rev. 2.2 — 5 December 2011

Product data sheet

1. General description

The SSL2103 is a Switched Mode Power Supply (SMPS) controller IC that operates in combination with a phase cut dimmer directly from the rectified mains. It is designed to drive LED devices. The device includes a circuit to allow direct start-up from the rectified mains voltage.

For dimmer applications, an integrated dedicated circuitry optimizes the dimming curve.

- SSL2101: fully integrated LED driver for lamps up to 10 W
- SSL2102: fully integrated LED driver for lamps up to 25 W
- SSL2103: gives the application designer flexibility to:
 - Use an external power switch to allow the IC to provide any power
 - Use an external bleeder transistors to provide extended dimmer interoperability

2. Features and benefits

- Easy migration to existing lighting control infrastructure
- Supports most available dimming solutions
- Optimized efficiency with valley switching managed by a built-in circuitry
- Demagnetization detection
- OverTemperature Protection (OTP)
- Short-Winding Protection (SWP) and OverCurrent Protection (OCP)
- Internal V_{CC} generation allowing start-up from the rectified mains voltage
- Natural dimming curve by logarithmic correction, down to 1 %
- Suitable for flyback and buck applications

3. Applications

- SSL applications with various power requirements
- LED modules such as LED spots and down-lights
- LED strings suitable for retail displays, etc.



Dimmable Greenchip controller for LED lighting

4. Quick reference data

Table 1. Quick reference data

Symbol	Parameter	Conditions	Min	Тур	Max	Unit
V_{CC}	supply voltage	$V_{DRAIN} > 60 V$	<u>[1]</u> 12	20	28	V
f _{osc}	oscillator frequency		10	100	130	kHz
I _{DRAIN}	current on pin DRAIN	V _{DRAIN} > 60 V; with auxiliary supply	-	30	125	μΑ
δ_{min}	minimum duty factor		-	0	-	%
δ_{max}	maximum duty cycle	PWMLIMIT= 3 V	-	75	-	%
T _{amb}	ambient temperature		-40	-	+100	°C

^[1] $V_{CC} = 20 \text{ V}$ minimum to meet all characteristics.


5. Ordering information

Table 2. Ordering information

Type number	Package		
	Name	Description	Version
SSL2103T	SO14	plastic small outline package; 14 leads; body width 3.9 mm	SOT108-1

Dimmable Greenchip controller for LED lighting


6. Block diagram



Dimmable Greenchip controller for LED lighting

7. Pinning information

7.1 Pinning



7.2 Pin description

Table 3. Pin description

Symbol	Pin	Description
SB_DRV	1	strong bleeder switch drive
WB_DRV	2	weak bleeder switch drive
V _{CC}	3	supply voltage
GND	4	ground
BRIGHTNESS	5	brightness input
RC2	6	setting for frequency reduction
RC	7	frequency setting
PWMLIMIT	8	PWM limit input
ISENSE	9	current sense input for WBLEED
AUX	10	input for voltage from auxiliary winding for timing (demagnetization)
SOURCE	11	current sense input of external power switch
PWR_DRV	12	power switch drive
DRAIN	13	drain of external power switch; input for start-up current and valley sensing
HVDET	14	input for high voltage sensing

Dimmable Greenchip controller for LED lighting

8. Functional description

The SSL2103 is an LED driver IC that operates directly from the rectified mains. The SSL2103 uses on-time mode control and frequency control to control the LED brightness. The BRIGHTNESS and PWMLIMIT input of the IC can be used to control the LED light output in combination with an external dimmer. The PWMLIMIT input can also be used for Thermal Lumen Management (TLM) and for precision LED current control.

8.1 Start-up and Under Voltage Lock Out (UVLO)

Initially, the IC is self-supplying from the rectified mains voltage. The IC starts switching as soon as the voltage on pin V_{CC} passes the $V_{CC(startup)}$ level. The supply can be taken over by the auxiliary winding of the transformer as soon as V_{CC} is high enough and the supply from the line is stopped for high efficiency operation. Alternatively the IC can be supplied via a bleeder resistor connected to a high voltage.

Remark: The maximum V_{CC} voltage rating of the IC must be considered.

8.2 Oscillator

An oscillator inside the IC provides the timing for the switching converter logic.


The frequency of the oscillator is set by the external resistors and the capacitor on pin RC and pin RC2. The external capacitor is charged rapidly to the $V_{RC(max)}$ level and, starting from a new primary stroke, discharges to the $V_{RC(min)}$ level. Because the discharge is exponential, the relative sensitivity of the duty factor to the regulation voltage at low duty factor, is almost equal to the sensitivity at high duty factors. This results in a more constant gain over the duty factor range, compared to Pulse Width Modulated (PWM) systems with a linear sawtooth oscillator. Stable operation at low duty factors is easily achieved. The frequency of the converter when $V_{BRIGHTNESS}$ is high can be calculated using Equation 1:

$$RC = \frac{1}{3.5} \cdot \left(\frac{1}{f_{osc}} - t_{charge} \right) \tag{1}$$

R equals the parallel resistance of both oscillator resistors. C is the capacitor connected at the RC pin (pin 7).


The BRIGHTNESS input controls the frequency reduction mode. Figure 3 shows that the oscillator switches over from an RC curve with R1/R2, to R1 only. A low BRIGHTNESS voltage will reduce the switching frequency.

Dimmable Greenchip controller for LED lighting



A typical RC waveform is shown in <u>Figure 4</u>. The RC switch-over threshold is controlled by the BRIGHTNESS pin.

To ensure that the capacitor can be charged within the charge time, the value of the oscillator capacitor should be limited to 1 nF. Due to leakage current, the value of the resistor connected between the RC pin and the ground should be limited to a maximum of 220 $k\Omega$.



8.3 Duty factor control

The duty factor is controlled by an internally regulated voltage and the oscillator signal on pin RC. The internal regulation voltage is set by the voltage on the PWMLIMIT pin.


A low PWMLIMIT voltage will results in a low on-time for the external power switch. The minimum duty factor of the switched mode power supply can be set to $0\,\%$. The maximum duty factor is set to $75\,\%$.

8.4 Bleeder for dimming applications

The SSL2103 IC contains some circuitry intended for mains dimmer compatibility. This circuitry can drive two external current sinks, called bleeders. A strong bleeder is used for zero-cross reset of the dimmer and TRIAC latching. A weak bleeder is added to maintain the hold current through the dimmer.

Dimmable Greenchip controller for LED lighting

The SB_DRV output is activated when the maximum voltage on pin HVDET is below the $V_{th(SBLEED)}$ level (52 V typically). The WB_DRV output is activated as soon as the voltage on pin ISENSE exceeds the $V_{th(high)(ISENSE)}$ level (–100 mV typically). The WB_DRV output is deactivated when the ISENSE voltage drops below the $V_{th(low)(ISENSE)}$ level (–250 mV typically). The WB_DRV output is also deactivated when the strong bleeder switch is switched on. See Figure 5.



8.5 Valley switching

A new cycle is started when the primary switch is switched on (see <u>Figure 6</u>). After a time determined by the oscillator voltage, RC and the internal regulation level, the switch is turned off and the secondary stroke starts. The internal regulation level is determined by the voltage on pin PWMLIMIT.

After the secondary stroke, the drain voltage shows an oscillation with a frequency of approximately:

$$\frac{1}{2 \times \pi \times \sqrt{(L_p \times C_p)}}\tag{2}$$

where:

L_p = primary self inductance


C_p = parasitic capacitance on drain node

As soon as the oscillator voltage is high again and the secondary stroke has ended, the circuit waits for a low drain voltage before starting a new primary stroke.


<u>Figure 6</u> shows the drain voltage together with the valley signal, the signal indicating the secondary stroke and the RC voltage.

The primary stroke starts some time before the actual valley at low ringing frequencies, and some time after the actual valley at high ringing frequencies.

Dimmable Greenchip controller for LED lighting



<u>Figure 7</u> shows a typical curve for a reflected output voltage N at an output voltage of 80 V. This voltage is the output voltage transferred to the primary side of the transformer with the factor N (determined by the turns ratio of the transformer). It shows that the system switches exactly at minimum drain voltage for ringing frequencies of 480 kHz, thus reducing the switch-on losses to a minimum. At 130 kHz, the next primary stroke is started at 33° before the valley. The switch-on losses are still reduced significantly.



Dimmable Greenchip controller for LED lighting

8.6 Demagnetization

The system operates in discontinuous conduction mode if the AUX pin is connected. As long as the secondary stroke has not ended, the oscillator will not start a new primary stroke. During the first $t_{\text{sup}(xfmr_ring)}$ seconds, demagnetization recognition is suppressed. This suppression may be necessary in applications where the transformer has a large leakage inductance and at low output voltages.

8.7 Overcurrent protection

The cycle-by-cycle peak drain current limit circuit uses the external source resistor R_{SENSE} to measure the current. The circuit is activated after the leading edge blanking time $t_{\text{leb}}.$ The protection circuit limits the source voltage over the $R_{\text{SENSE}}{}^1$ resistor to $V_{\text{th(ocp)SOURCE}},$ and thus limits the primary peak current.

8.8 Short-winding protection

The short-winding protection circuit is also activated after the leading edge blanking time. If the source voltage exceeds the short-winding protection threshold voltage $V_{th(swp)SOURCE}$, the IC stops switching. Only a power-on reset will restart normal operation. The short-winding protection also protects in case of a secondary diode short circuit.

8.9 Overtemperature protection

Accurate temperature protection is provided in the device. When the junction temperature exceeds the thermal shut-down temperature, the IC stops switching. During thermal protection, the IC current is lowered to the start-up current. The IC continues normal operation as soon as the overtemperature situation has disappeared.

SSL2103

^{1.} R_{SENSE} is the resistor between the SOURCE pin and GND

Dimmable Greenchip controller for LED lighting

9. Limiting values

Table 4. Limiting values

In accordance with the Absolute Maximum Rating System (IEC 60134). All voltages are measured with respect to ground; positive currents flow into the device.

Symbol	Parameter	Conditions		Min	Max	Unit
Voltages						
V _{CC}	supply voltage	continuous	<u>[1]</u>	-0.4	+28	V
V_{RC}	voltage on pin RC		[1]	-0.4	+3	V
V _{RC2}	voltage on pin RC2			-0.4	+3	V
V _{BRIGHTNESS}	voltage on pin BRIGHTNESS			-0.4	+5	V
V _{PWMLIMIT}	voltage on pin PWMLIMIT			-0.4	+5	V
V _{SOURCE}	voltage on pin SOURCE			-0.4	+5	V
V _{DRAIN}	voltage on pin DRAIN	T _{amb} = 25 °C		-0.4	+600	V
V _{HVDET}	voltage on pin HVDET	T _{amb} = 25 °C		-0.4	+600	V
Currents						
I _{ISENSE}	current on pin ISENSE		[2]	-20	+5	mΑ
I _{AUX}	current on pin AUX		[2]	-10	+5	mΑ
I _{SB_DRV}	current on pin SB_DRV				+3.6	mΑ
I _{WB_DRV}	current on pin WB_DRV				+3.6	mΑ
General						
P _{tot}	total power dissipation	T _{amb} = 70 °C		-	250	mW
T _{stg}	storage temperature			-55	+150	°C
T _{amb}	ambient temperature			-40	+100	°C
Tj	junction temperature			-40	+150	°C
V _{ESD}	electrostatic discharge voltage	human body model;	<u>[3]</u>			
		Pins 13 and 14		-1000	+1000	V
		All other pins		-2000	+2000	V
		charged device model	<u>[4]</u>	-500	+500	V

^[1] Pins V_{CC} and RC cannot be current driven.

10. Thermal characteristics

Table 5. Thermal characteristics

Symbol	Parameter	Conditions	Тур	Unit
R _{th(j-a)}	thermal resistance from junction to ambient	in free air, on JESD51-3 board	123	K/W
Ψ_{j-top}	thermal characterization parameter from junction to top	in free air, on JESD51-3 board	7	K/W

^[2] Pins ISENSE and AUX cannot be voltage driven.

^[3] Human body model: equivalent to discharging a 100 pF capacitor through a 1.5 k Ω series resistor.

^[4] Charged device model: equivalent to charging the IC up to 1 kV and the subsequent discharging of each pin down to 0 V over a 1 Ω resistor.

Dimmable Greenchip controller for LED lighting

11. Characteristics

Table 6. Characteristics

 T_{amb} = 25 °C; no overtemperature; all voltages are measured with respect to ground; currents are positive when flowing into the IC; V_{CC} = 20 V and PWMLIMIT and BRIGHTNESS pins are disconnected unless otherwise specified. Typical frequency 100 kHz.

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
Supply							
I _{CC}	supply current	normal operation; bleeders disconnected; V _{DRAIN} = 60 V;		-	1.8	-	mA
I _{CC(ch)}	charge supply current	$V_{DRAIN} > 60 \text{ V}; V_{CC} = 0 \text{ V}$		-6	-4.5	-	mΑ
V _{CC}	supply voltage	V _{DRAIN} > 60 V	[1]	12	20	28	V
V _{CC(startup)}	start-up supply voltage			-	10.25	-	V
V _{CC(UVLO)}	undervoltage lockout supply voltage			-	8.2	-	V
I _{DRAIN}	current on pin DRAIN	V _{DRAIN} > 60 V; with auxiliary supply		-	30	125	μΑ
V _{DRAIN}	voltage on pin DRAIN			40	-	600	V
Pulse width mod	lulator						
δ_{min}	minimum duty factor			-	0	-	%
δ_{max}	maximum duty cycle	PWMLIMIT= 3 V		-	75	-	%
SOPS							
V _{det(demag)}	demagnetization detection voltage			50	100	150	mV
t _{sup(xfmr_ring)}	transformer ringing suppression time	at start of secondary stroke		1.0	1.5	2.0	μS
RC oscillator							
V _{RC(min)}	minimum voltage on pin RC			60	75	90	mV
V _{RC(max)}	maximum voltage on pin RC			2.4	2.5	2.6	V
t _{ch(RC)}	charge time on pin RC			-	1	-	μS
f _{osc}	oscillator frequency			10	100	130	kHz
I _{BRIGHTNESS}	current on pin BRIGHTNESS	V _{BRIGHTNESS} = 0 V		-20	-24	-28	μΑ
Driver bleeder							
$V_{th(HVDET)}$	threshold voltage on pin HVDET			46	52	56	V
$V_{th(low)ISENSE}$	low threshold voltage on pin ISENSE			-	-250	-	mV
$V_{th(high)ISENSE}$	high threshold voltage on pin ISENSE			-	-100	-	mV
I _{SB_DRV}	current on pin SB_DRV	$V_{SB_DRV} < 9 V$		-	3.2	3.6	mA
I _{WB_DRV}	current on pin WB_DRV	V _{WB_DRV} < 9 V		-	3.2	3.6	mA
V _{SB_DRV}	voltage on pin SB_DRV	$I_{SB_DRV} = 0$		-	-	12	V
		I _{SB_DRV} = 2.5 mA		-	10	-	V
		during V _{CC} start-up; I _{SB_DRV} = 2.5 mA	[2]	5.5	-	-	V
V_{WB_DRV}	voltage on pin WB_DRV	$I_{WB_DRV} = 0$		-	-	12	V
_	-	$I_{WB_DRV} = 2.5 \text{ mA}$		-	10	-	V

Dimmable Greenchip controller for LED lighting

 Table 6.
 Characteristics ...continued

 T_{amb} = 25 °C; no overtemperature; all voltages are measured with respect to ground; currents are positive when flowing into the IC; V_{CC} = 20 V and PWMLIMIT and BRIGHTNESS pins are disconnected unless otherwise specified. Typical frequency 100 kHz.

Symbol	Parameter	Conditions		Min	Тур	Max	Unit
Duty factor regu	ılator: pin PWMLIMIT						
I _{PWMLIMIT}	current on pin PWMLIMIT			-25	-	-18	μΑ
V _{PWMLIMIT}	voltage on pin PWMLIMIT	maximum duty cycle threshold $V_{\text{BRIGHTNESS}} = 3 \text{ V}$		-	2.6	-	V
		minimum duty cycle threshold $V_{BRIGHTNESS} = 3 V$		-	0.45	-	V
Valley switching	I						
$(\Delta V/\Delta t)_{vrec}$	valley recognition voltage change with time	minimum absolute value	[3]	-	100	-	V/μs
f _{ring}	ringing frequency	$N \times V_O = 100 \text{ V}$		200	500	800	kHz
$t_{d(vrec\text{-}swon)}$	valley recognition to switch-on delay time			-	150	-	ns
Current and sho	ort circuit winding protection						
$V_{th(ocp)}$ SOURCE	overcurrent protection threshold voltage on pin SOURCE	$dV/dt = 0.1 V/\mu s$		0.46	0.50	0.53	V
$V_{th(swp)}$ SOURCE	short-winding protection threshold voltage on pin SOURCE	$dV/dt = 0.1 V/\mu s$		-	1.5	-	V
$t_{\text{d(ocp-swoff)}}$	delay time from overcurrent protection to switch-off	$dV/dt = 0.5 V/\mu s$		-	160	185	ns
t _{leb}	leading edge blanking time			250	350	450	ns
FET driver outpo	ut stage						
$V_{O(PWR_DRV)}$	output Voltage on pin PWR_DRV			-	12	V_{CC}	V
$t_{r(PWR_DRV)}$	rise time on pin PWR_DRV	With maximum input capacitance 4.7 nF on pin PWR_DRV; $V_{CC} = 20 \text{ V}$		-	210	-	ns
$t_{f(PWR_DRV)}$	fall time on pin PWR_DRV	With maximum input capacitance 4.7 nF on pin PWR_DRV; $V_{CC} = 20 \text{ V}$		-	210	-	ns
Temperature pro	otection						
T_{otp}	overtemperature protection threshold	junction temperature		150	160	170	°C
T _{otp(hys)}	overtemperature protection trip hysteresis	junction temperature		-	7	-	°C

^[1] $V_{CC} = 20 \text{ V}$ minimum to meet all characteristics.

^[2] SB_DRV is active during V_{CC} start-up.

^[3] Voltage change in time for valley recognition.

Dimmable Greenchip controller for LED lighting




Fig 8. Typical frequency as a function of voltage on pin BRIGHTNESS (with RC value given in <u>Figure 3</u>)






Fig 9. Turn-on time as a function of voltage on pin PWMLIMIT (with RC value given in Figure 3)

Dimmable Greenchip controller for LED lighting




Dimmable Greenchip controller for LED lighting

12. Application information



Dimmable Greenchip controller for LED lighting



Further application information can be found in the SSL2103 application notes.


SSL2103 NXP Semiconductors

Dimmable Greenchip controller for LED lighting

13. Package outline

SO14: plastic small outline package; 14 leads; body width 3.9 mm

SOT108-1



UNIT	A max.	A ₁	A ₂	А3	bp	С	D ⁽¹⁾	E ⁽¹⁾	е	HE	L	Lp	Q	٧	w	у	Z ⁽¹⁾	θ
mm	1.75	0.25 0.10	1.45 1.25	0.25	0.49 0.36	0.25 0.19	8.75 8.55	4.0 3.8	1.27	6.2 5.8	1.05	1.0 0.4	0.7 0.6	0.25	0.25	0.1	0.7 0.3	8°
inches	0.069	0.010 0.004	0.057 0.049	0.01		0.0100 0.0075		0.16 0.15	0.05	0.244 0.228	0.041	0.039 0.016		0.01	0.01	0.004	0.028 0.012	0°

Note

1. Plastic or metal protrusions of 0.15 mm (0.006 inch) maximum per side are not included.

OUTLINE		REFER	ENCES	EUROPEAN	ISSUE DATE	
VERSION	IEC	JEDEC	JEITA	PROJECTION	ISSUE DATE	
SOT108-1	076E06	MS-012			99-12-27 03-02-19	

Fig 13. Package outline SOT108-1 (SO14)

SSL2103 NXP Semiconductors

Dimmable Greenchip controller for LED lighting

14. Revision history

Table 7. **Revision history**

Decument ID	Dologoo doto	Data about status	Change nation	Cumanaadaa						
Document ID	Release date	Data sheet status	Change notice	Supersedes						
SSL2103 v.2.2	20111205	Product data sheet	-	SSL2103 v.2.1						
Modifications:	 GreenChip 	trademark has been added.								
	 Section 1 "0 	General description" has bee	n updated.							
	 Section 2 "I 	 Section 2 "Features and benefits" has been updated. 								
	 Section 3 "/ 	Applications" has been updat	ed.							
SSL2103 v.2.1	20110825	Product data sheet	-	SSL2103 v.2.0						
SSL2103 v.2	20101125	Product data sheet	-	SSL2103 v.1						
SSL2103 v.1	20101011	Preliminary data sheet	-	-						

Dimmable Greenchip controller for LED lighting

15. Legal information

15.1 Data sheet status

Document status[1][2]	Product status[3]	Definition
Objective [short] data sheet	Development	This document contains data from the objective specification for product development.
Preliminary [short] data sheet	Qualification	This document contains data from the preliminary specification.
Product [short] data sheet	Production	This document contains the product specification.

- [1] Please consult the most recently issued document before initiating or completing a design.
- [2] The term 'short data sheet' is explained in section "Definitions"
- [3] The product status of device(s) described in this document may have changed since this document was published and may differ in case of multiple devices. The latest product status information is available on the Internet at URL http://www.nxp.com.

15.2 Definitions

Draft — The document is a draft version only. The content is still under internal review and subject to formal approval, which may result in modifications or additions. NXP Semiconductors does not give any representations or warranties as to the accuracy or completeness of information included herein and shall have no liability for the consequences of use of such information.

Short data sheet — A short data sheet is an extract from a full data sheet with the same product type number(s) and title. A short data sheet is intended for quick reference only and should not be relied upon to contain detailed and full information. For detailed and full information see the relevant full data sheet, which is available on request via the local NXP Semiconductors sales office. In case of any inconsistency or conflict with the short data sheet, the full data sheet shall prevail.

Product specification — The information and data provided in a Product data sheet shall define the specification of the product as agreed between NXP Semiconductors and its customer, unless NXP Semiconductors and customer have explicitly agreed otherwise in writing. In no event however, shall an agreement be valid in which the NXP Semiconductors product is deemed to offer functions and qualities beyond those described in the Product data sheet.

15.3 Disclaimers

Limited warranty and liability — Information in this document is believed to be accurate and reliable. However, NXP Semiconductors does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information and shall have no liability for the consequences of use of such information.

In no event shall NXP Semiconductors be liable for any indirect, incidental, punitive, special or consequential damages (including - without limitation - lost profits, lost savings, business interruption, costs related to the removal or replacement of any products or rework charges) whether or not such damages are based on tort (including negligence), warranty, breach of contract or any other legal theory.

Notwithstanding any damages that customer might incur for any reason whatsoever, NXP Semiconductors' aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the *Terms and conditions of commercial sale* of NXP Semiconductors.

Right to make changes — NXP Semiconductors reserves the right to make changes to information published in this document, including without limitation specifications and product descriptions, at any time and without notice. This document supersedes and replaces all information supplied prior to the publication hereof.

Suitability for use — NXP Semiconductors products are not designed, authorized or warranted to be suitable for use in life support, life-critical or safety-critical systems or equipment, nor in applications where failure or

malfunction of an NXP Semiconductors product can reasonably be expected to result in personal injury, death or severe property or environmental damage. NXP Semiconductors accepts no liability for inclusion and/or use of NXP Semiconductors products in such equipment or applications and therefore such inclusion and/or use is at the customer's own risk.

Applications — Applications that are described herein for any of these products are for illustrative purposes only. NXP Semiconductors makes no representation or warranty that such applications will be suitable for the specified use without further testing or modification.

Customers are responsible for the design and operation of their applications and products using NXP Semiconductors products, and NXP Semiconductors accepts no liability for any assistance with applications or customer product design. It is customer's sole responsibility to determine whether the NXP Semiconductors product is suitable and fit for the customer's applications and products planned, as well as for the planned application and use of customer's third party customer(s). Customers should provide appropriate design and operating safeguards to minimize the risks associated with their applications and products.

NXP Semiconductors does not accept any liability related to any default, damage, costs or problem which is based on any weakness or default in the customer's applications or products, or the application or use by customer's third party customer(s). Customer is responsible for doing all necessary testing for the customer's applications and products using NXP Semiconductors products in order to avoid a default of the applications and the products or of the application or use by customer's third party customer(s). NXP does not accept any liability in this respect.

Limiting values — Stress above one or more limiting values (as defined in the Absolute Maximum Ratings System of IEC 60134) will cause permanent damage to the device. Limiting values are stress ratings only and (proper) operation of the device at these or any other conditions above those given in the Recommended operating conditions section (if present) or the Characteristics sections of this document is not warranted. Constant or repeated exposure to limiting values will permanently and irreversibly affect the quality and reliability of the device.

Terms and conditions of commercial sale — NXP Semiconductors products are sold subject to the general terms and conditions of commercial sale, as published at http://www.nxp.com/profile/terms, unless otherwise agreed in a valid written individual agreement. In case an individual agreement is concluded only the terms and conditions of the respective agreement shall apply. NXP Semiconductors hereby expressly objects to applying the customer's general terms and conditions with regard to the purchase of NXP Semiconductors products by customer.

No offer to sell or license — Nothing in this document may be interpreted or construed as an offer to sell products that is open for acceptance or the grant, conveyance or implication of any license under any copyrights, patents or other industrial or intellectual property rights.

Export control — This document as well as the item(s) described herein may be subject to export control regulations. Export might require a prior authorization from competent authorities.

SSL2103

Dimmable Greenchip controller for LED lighting

Quick reference data — The Quick reference data is an extract of the product data given in the Limiting values and Characteristics sections of this document, and as such is not complete, exhaustive or legally binding.

Non-automotive qualified products — Unless this data sheet expressly states that this specific NXP Semiconductors product is automotive qualified, the product is not suitable for automotive use. It is neither qualified nor tested in accordance with automotive testing or application requirements. NXP Semiconductors accepts no liability for inclusion and/or use of non-automotive qualified products in automotive equipment or applications.

In the event that customer uses the product for design-in and use in automotive applications to automotive specifications and standards, customer (a) shall use the product without NXP Semiconductors' warranty of the product for such automotive applications, use and specifications, and (b)

whenever customer uses the product for automotive applications beyond NXP Semiconductors' specifications such use shall be solely at customer's own risk, and (c) customer fully indemnifies NXP Semiconductors for any liability, damages or failed product claims resulting from customer design and use of the product for automotive applications beyond NXP Semiconductors' standard warranty and NXP Semiconductors' product specifications.

15.4 Trademarks

Notice: All referenced brands, product names, service names and trademarks are the property of their respective owners.

GreenChip — is a trademark of NXP B.V.

16. Contact information

For more information, please visit: http://www.nxp.com

For sales office addresses, please send an email to: salesaddresses@nxp.com

SSL2103 NXP Semiconductors

Dimmable Greenchip controller for LED lighting

17. Contents

1	General description	. 1
2	Features and benefits	. 1
3	Applications	. 1
4	Quick reference data	2
5	Ordering information	2
6	Block diagram	
7	Pinning information	
7.1	Pinning	
7.2	Pin description	4
8	Functional description	5
8.1	Start-up and Under Voltage Lock Out (UVLO) .	5
8.2	Oscillator	
8.3	Duty factor control	
8.4	Bleeder for dimming applications	
8.5	Valley switching	
8.6	Demagnetization	
8.7	Overcurrent protection	
8.8 8.9	Short-winding protection	
9	Limiting values	
10	Thermal characteristics	
11	Characteristics	11
12	Application information	15
13	Package outline	17
14	Revision history	18
15	Legal information	19
15.1	Data sheet status	19
15.2	Definitions	19
15.3	Disclaimers	19
15.4	Trademarks	20
16	Contact information	20
17	Contents	21

Please be aware that important notices concerning this document and the product(s) described herein, have been included in section 'Legal information'.

© NXP B.V. 2011.

All rights reserved.

For more information, please visit: http://www.nxp.com For sales office addresses, please send an email to: salesaddresses@nxp.com

Date of release: 5 December 2011 Document identifier: SSL2103

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

NXP:

SSL2103T/1,518